Lampu Emergency EXIT SAMCOM ELS-28S Boxster









Emergency EXIT Sign 2x8watt Boxster SAMCOM ELS-28S

Rating: Not Rated Yet
Ask a question about this product

ManufacturerSamcom

Description

Lampu Emergency EXIT Samcom ELS-28S adalah lampu tanda keluar merupakan syarat standar keamanan suatu gedung sebagai penunjuk arah evakuasi, model boxster ini dengan kekuatan 2x8watt memberikan penerangan maksimal untuk pengunjung melihat tanda keluar jika terjadi keadaan darurat.

Lampu darurat exit ini banyak dipakai untuk gedung perkantoran, gedung rumah sakit, mall atau supermarket, tanda keluar area bandara dan sebagainya.

Spesifikasi model ELS-28 merk SAMCOM ini sebagai berikut:

- Input voltage 230Vac, 50/60Hz ±10% A:0.34 PF:0.77
- Battery 2,4v 2,5Ah High Temperature rated Nickel Cadmium cell or others
- Rated Period > 2 hrs, 3 hrs or others
- Mode Maintained
- Operation Temperature ta 40 °C
- Power Consumption < 4VA
- Charged Monitor Bi-Color (Green: Normal / Red: Fault)
- Recharge Period 16 ~ 24 hrs
- Emergency Luminance > 8 cd/m²
- Electromanetic Field 17m gause @ 0,1m
- Charger Hybrid Controlled charger
- Protection Low volt cut-off to prevent battery over discharged, Incoming AC Fuse & Battery DC fuse, Tropical climate protection coating on hybrid control circuit
- Contruction Electrode galvanised sheet steel with epoxy powder coating, 20mm Ø K/O hole, Fire Retardant Acrylic Opal Diffuser
- Dimension 355mm (L) x 58mm (W) x 287mm (H)
- Weight 2,30 kg (net) / 2,50 kg (gross)
- Packing one unit per canton

Reviews

There are yet no reviews for this product.